

PE98A655

LASER SENSORS • THROUGH-BEAM SENSORS RECEIVERS

Optical sensors function contactlessly. They detect objects independent of their characteristics (e.g., shape, color, surface structure, material). The basic operating principle is based on the transmission and reception of light. There are three different versions: 1. The through-beam sensor consists of two separate devices, a transmitter and a receiver that are aligned with one another. If the light beam between the two devices is interrupted, the switching output integrated in the receiver changes its status. 2. With the retro-reflective sensor, the transmitter and receiver are located in one device. The emitted light beam is reflected back to the receiver by a reflector that is to be mounted opposite the device. As soon as the light beam is interrupted, the switching output integrated in the device changes its status. 3. With the diffuse reflection sensor, the transmitter and receiver are in one device. The emitted light beam is reflected by the object that is to be detected. As soon as the receiver detects the reflected light, the switching output integrated in the device changes its status.

MECHANICAL DATA

| | |
|-----------------------------|------------------|
| Ambient temperature | -20 °C ... 50 °C |
| Degree of protection (IP) | IP67 |
| Housing coating | Nickel-plated |
| Housing design | Cuboid |
| Housing material | Brass |
| Material of optical surface | Glass |
| Sensor height | 34 mm |
| Sensor length | 122 mm |
| Sensor width | 34 mm |
| Storage temperature | 85 °C |
| Thread length | 12 mm |

ELECTRICAL DATA

| | |
|-----------------------------|---------------------|
| Function test | Yes |
| IO-Link compatible | No |
| Max. output current | 100 mA |
| Measuring range | 5 m |
| No-load current | 30 mA |
| No-load current, receiver | 30 mA |
| Number of pins | 4 |
| Operating voltage | 12 V ... 32 V |
| Rated switching distance | 5000 mm |
| Relative repeat accuracy | 15 µm |
| Reverse polarity protection | Yes |
| Scanning function | Light-/dark-on mode |
| Setting procedure | Manual adjustment |
| Short-circuit-proof | Yes |

ELECTRICAL DATA

| | |
|-------------------------------|---------------|
| Switching frequency | 25000 Hz |
| Type of analog output | 0 V ... 10 V |
| Type of electrical connection | Connector M12 |
| Type of input voltage | DC |
| Type of switching output | PNP/NPN |
| Voltage drop | 2 V |
| Voltage type | DC |
| With LED display (signal) | Yes |

OPTICAL DATA

| | |
|--------------------------|----------------------------------|
| Aperture length | 30 mm |
| Aperture width | 0.5 mm |
| Filter | Interference / polarizing filter |
| Light beam form | Line |
| Light source | Laser diode, red light |
| Resolution | 150 µm |
| Wavelength of the sensor | 670 nm |

OTHER DATA

| | |
|---|----------|
| Scope of delivery of the one-way system | Receiver |
|---|----------|

DIMENSIONAL DRAWING**INSTALLATION**

Mounting / Installation may only be carried out by a qualified electrician!

DISPOSAL**SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!