

## OY350132

### SAFETY SYSTEMS • LIGHT CURTAINS - FINGER PROTECTION

safety light curtains are suitable for the protection of hazardous areas on machines according to the applicable standards. there are three groups of devices: body protection (2, 3 and 4 rays), hand protection (resolution 30mm) and finger protection (resolution 14mm). each group has devices with different protection field heights. Often these systems are used in conveyors, welding robots as well as cutting and bending machines



#### MECHANICAL DATA

Ambient temperature	-10 °C ... 55 °C
Degree of protection (IP)	IP65
Housing material	Aluminium with macrolon plastic cover panel
Protected field height	455 mm
Sensor height	40 mm
Sensor length	550 mm
Sensor width	35 mm

#### ELECTRICAL DATA

Cascadable	No
Clock control possible	No
Equipment protection class	Protection class 3
Max. output current at safe output	250 mA
No-load current, receiver	100 mA
No-load current, transmitter	70 mA
Number of pins, receiver	8
Number of pins, transmitter	4
Number of safe semiconductor outputs	2
Override possible	Yes
Rated control supply voltage $U_s$ at DC	24 V ... 24 V
Reaction time	26 ms
Reverse polarity protection	Yes
Short-circuit-proof	Yes
Suitable for safety functions	Yes
Suppression possible	No
Switching output type of the OSSD	PNP
Switching voltage of OSSD at state "high"	24 V
Type of electrical connection	Connector M12
Type of switching function	Normally open contact (NO)
Voltage type	DC
With LED display (7 segment)	Yes

## ELECTRICAL DATA

With monitoring function of downstream devices	No
With muting function	Yes
With restart lock	Yes

## OPTICAL DATA

Beam spacing	7 mm
Detection capability for samples	14 mm
Finger protection (< 14mm)	Yes
Number of beams	63
Protected field range	6 m
Resolution of the light curtain	14 mm
Wavelength of the sensor	880 nm

## OTHER DATA

Explosion protection category for dust	None
Explosion protection category for gas	None
Safety category	Category 4
Safety type in acc. with IEC 61496-1	4
Scope of delivery of the one-way system	Transmitter and receiver
With beam coding	Yes

## CONNECTION



## DIMENSIONAL DRAWING



## INSTALLATION



Mounting / Installation may only be carried out by a qualified electrician!

## DISPOSAL



## **SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!