

**PESI0083****LASER SENSORS • THROUGH-BEAM SENSORS RECEIVERS**

Optical sensors function contactlessly. They detect objects independent of their characteristics (e.g., shape, color, surface structure, material). The basic operating principle is based on the transmission and reception of light. There are three different versions: 1. The through-beam sensor consists of two separate devices, a transmitter and a receiver that are aligned with one another. If the light beam between the two devices is interrupted, the switching output integrated in the receiver changes its status. 2. With the retro-reflective sensor, the transmitter and receiver are located in one device. The emitted light beam is reflected back to the receiver by a reflector that is to be mounted opposite the device. As soon as the light beam is interrupted, the switching output integrated in the device changes its status. 3. With the diffuse reflection sensor, the transmitter and receiver are in one device. The emitted light beam is reflected by the object that is to be detected. As soon as the receiver detects the reflected light, the switching output integrated in the device changes its status.

**MECHANICAL DATA**

Ambient temperature	0 °C ... 50 °C
Degree of protection (IP)	IP67
Housing coating	Anodised
Housing design	Cuboid
Housing material	Aluminium
Reflector included in the scope of delivery	No
Sensor height	17 mm
Sensor length	68 mm
Sensor width	12 mm
Storage temperature	85 °C
Storage temperature	-20 °C

**ELECTRICAL DATA**

Connection to amplifier	Yes
IO-Link compatible	No
Laser power	1 mW
Measuring range	10 m
No-load current	20 mA
Number of pins	4
Operating voltage	12 V ... 12 V
Rated switching distance	10000 mm
Relative repeat accuracy	20 µm
Setting procedure	Parameterization
Switching frequency	1000 Hz
Type of analog output	0 V ... 10 V
Type of electrical connection	Connector M8
Type of input voltage	DC

**ELECTRICAL DATA**

Voltage type	DC
With time function	No

**OPTICAL DATA**

Aperture length	6 mm
Aperture width	2 mm
Filter	Interference filter
Light beam form	Line
Light source	Laser diode, red light
Wavelength of the sensor	670 nm

**OTHER DATA**

Scope of delivery of the one-way system	Receiver
---	----------

**DIMENSIONAL DRAWING****INSTALLATION**

Mounting / Installation may only be carried out by a qualified electrician!

**DISPOSAL****SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!