

PS180024

LASER SENSORS • THROUGH-BEAM SENSORS TRANSMITTERS

Optical sensors function contactlessly. They detect objects independent of their characteristics (e.g., shape, color, surface structure, material). The basic operating principle is based on the transmission and reception of light. There are three different versions: 1. The through-beam sensor consists of two separate devices, a transmitter and a receiver that are aligned with one another. If the light beam between the two devices is interrupted, the switching output integrated in the receiver changes its status. 2. With the retro-reflective sensor, the transmitter and receiver are located in one device. The emitted light beam is reflected back to the receiver by a reflector that is to be mounted opposite the device. As soon as the light beam is interrupted, the switching output integrated in the device changes its status. 3. With the diffuse reflection sensor, the transmitter and receiver are in one device. The emitted light beam is reflected by the object that is to be detected. As soon as the receiver detects the reflected light, the switching output integrated in the device changes its status.



MECHANICAL DATA

| | |
|-----------------------------|------------------------|
| Ambient temperature (MAX) | 50 °C |
| Ambient temperature (MIN) | -10 °C |
| Degree of protection (IP) | IP67 |
| Housing coating | Chromium-plated |
| Housing design | Cylinder, screw-thread |
| Housing material | Brass |
| Material of optical surface | PMMA |
| Storage temperature | 70 °C |
| Storage temperature | -25 °C |
| Thread length | 60 mm |
| Thread pitch | 1 mm |
| Thread size, metric | 18 |

ELECTRICAL DATA

| | |
|-------------------------------|---------------|
| Function test | Yes |
| Laser power | 1 mW |
| Measuring range | 60 m |
| No-load current | 30 mA |
| No-load current, transmitter | 30 mA |
| Number of pins | 4 |
| Operating voltage (MAX) | 30 V |
| Operating voltage (MIN) | 10 V |
| Rated switching distance | 60000 mm |
| Reverse polarity protection | Yes |
| Type of electrical connection | Connector M12 |
| Type of input voltage | DC |
| Voltage type | DC |

ELECTRICAL DATA

With LED display Yes

OPTICAL DATA

| | |
|--------------------------|------------------------|
| Laser class | 1 |
| Light beam form | Point |
| Light source | Laser diode, red light |
| Wavelength of the sensor | 650 nm |

OTHER DATA

| | |
|---|-------------|
| Scope of delivery of the one-way system | Transmitter |
|---|-------------|

DIMENSIONAL DRAWING**INSTALLATION**

Mounting / Installation may only be carried out by a qualified electrician!

DISPOSAL**SAFETY WARNINGS**

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!

Never use these devices in applications where the safety of a person depends on their functionality.