

FS906001

FILLING LEVEL SENSORS • CONDUCTIVE

Filling level and level sensors operate according to different measuring principles. The selection of the sensor depends on the medium to be detected and the ambient conditions. The material flow in a vibratory bowl can be excellently queried with inductive filling level sensors whose pendulum is moved by the material in the pot. The detection of liquid or solid media is, for instance, possible with capacitive filling level sensor technology. These work according to the principle of the condensator, the medium changes the dielectricity between two electrodes. The resulting change is converted into a digital output signal. A further alternative for the detection of filling levels of conductive media is provided by conductive filling level relays. The resistance between reference and measuring electrode is determined. If a set threshold is exceeded, a relay output switches.



MECHANICAL DATA

Ambient temperature (MAX)	100 °C
Ambient temperature (MIN)	-10 °C
Degree of protection (IP)	IP65
Housing design	Special construction
Housing material	Polyamid
Increased ambient temperatures > 80°C	Yes
Medium temperature (MAX)	100 °C
Medium temperature (MIN)	-20 °C
Pressure resistance	10 bar
Probe diameter	4 mm
Probe length	1000 mm
Sensing element material	Stainless steel 1.4571
Sensor diameter	40 mm
Sensor height	52 mm
Sensor length	1052 mm
Thread length	15 mm
Thread size, inches	1/2 inch
Type of process connection	G1/2 inch

ELECTRICAL DATA

Number of probes	1
Physical measurement principle	Conductive
Type of electrical connection	Clamp
Type of switching function	Amplifier
Type of switching output	Amplifier

DIMENSIONAL DRAWING

INSTALLATION



Mounting / Installation may only be carried out by a qualified electrician!

DISPOSAL



SAFETY WARNINGS

Before initial operation, please make sure to follow all safety instructions that may be provided in the product information!

Never use these devices in applications where the safety of a person depends on their functionality.